

Product



Features:

- 100~240V AC input
- Single Output
- 85% high efficiency
- 100% full load burn-in test
- Protection: OTP, OLP, OVP, SCP
- CE ROHS Certified
- 3 year warranty

ART-TR-324-60W

Applications:

- Indoor LED lighting
- LED office lighting
- LED commercial lighting
- LED decorative lighting



Specification

Product Code		ART-TR-324-60W12V-CL60	ART-TR-324-60W24V-CL60	ART-TR-324-60W48V-CL60
Output	DC Voltage	12V	24V	48V
	Rated Current	5A	2.5A	1.25A
	Current Range	0~5A	0~2.5A	0~1.25A
	Voltage tolerance	±5%	±5%	±5%
	Rated Power	60W	60W	60W
	Ripple & Noise	<120mVp-p	<240mVp-p	<240mVp-p
	Set-up, Rise Time	1500ms, 30ms / 230VAC		
Input	Input voltage range	100-240 VAC		
	Frequency Range	50~60Hz		
	AC Current	1.08A / 115VAC; 0.54A / 230VAC		
	Efficiency	86%	85%	85%
	PF	0.6		
Protection	Over Load	Above 110%-150% of rated power		
		Shut-down output voltage, auto recovery after fault condition is removed		
	Over Voltage	Above Max. Voltage (105% of rated voltage)		
		Shut-down output voltage, auto recovery after fault condition is removed		
	Over Temperature	Over 130°C detected on main IC control		
Ambiant	Working Temp. & humidity	"-20°C~+60°C, 20%~90%RH		
	Storage temp. & humidity	"-40°C~+85°C, 10%~95%RH		
Tesings	Withstand voltage	I/P-O/P: 1.5KVAC/1min; I/P-F/G: 1.5KVAC/1min; O/P-F/G: 0.5KVAC/1min;		
	Safety	GB4943 ;IEC60950-1; EN60950-1		
	EMC	EN 55032:2015+A11:2020 EN IEC 61000-3-2:2019+A1:2021 EN 61000-3-3:2013+A2:2021 EN55035:2017+A11:2020		
	LVD	EN60950-1:2006+A11:2009+A1:2010+A12:2011+A2:2013		
Others	Demension(L*W*H)	105*50*28mm		
	Packing	0.13kg/pcs, 70pcs/14kg/CTN		

Artisan Lighting Phuket Co.,Ltd.


100/364-5 Moo.5 Pracha-U-Thid Rd., Rassada, Muang, Phuket 83000 Thailand.

ONE-CALL : 081 688 8787 Line ID : @artisanlighting Email : support@artisanlighting.net / boi@artisanlighting.net


www.artisanlighting.net

Mechanical Structures

■ Side View




■ Vertical view




Wiring Diagram


1. Without Dimming




2. With Dimming



■ Derating Curve



■ Static characteristic



Notes:

1. The above mentioned data were measured at 230VAC input and 25°C.
2. Dis-connect the AC input before checking any mal-phenomenons.
3. Make sure the INPUT&OUPUT were in right situation before connected to power supply.
4. Datasheet for reference only. We suggest you take sampling before mass orders.

Artisan Lighting Phuket Co.,Ltd.

100/364-5 Moo.5 Pracha-U-Thid Rd., Rassada, Muang, Phuket 83000 Thailand.

ONE-CALL : 081 688 8787 Line ID : @artisanlighting Email : support@artisanlighting.net / boi@artisanlighting.net

www.artisanlighting.net